



The Power of Precision in WDM Wavelength Testing

HIGH-SPEED OPTICAL WAVELENGTH METER 828 Series

The fastest wavelength measurement available for WDM testing applications.

Bristol Instruments, the leader in optical wavelength measurement instrumentation, offers an interferometer-based wavelength meter that is designed to revolutionize WDM testing applications. The 828 Optical Wavelength Meter employs a unique Fizeau etalon technology that results in the ability to measure wavelength to an accuracy of ± 1 pm at an unmatched measurement rate of 1 kHz. This enables greater efficiency in the production of WDM components by reducing test times from hours to minutes. What's more, a time resolution of 1 ms results in the most detailed wavelength characterization of tunable lasers.



KEY FEATURES

- Wavelength measured to an accuracy of ± 1 pm.
- Automatic calibration with a built-in wavelength standard.
- Measurement confidence level of $\geq 99.7\%$.
- Traceable to NIST standards.
- Simultaneous measurement of optical power to ± 0.5 dB.
- High sensitivity of -40 dBm (0.1 μ W).
- Operates with CW and modulated signals.
- Fastest measurement rate of 1 kHz for reduced testing times.
- Time resolution of 1 ms for the most detailed wavelength characterization.
- Convenient touch-screen display reports measurement data in a variety of formats.
- Interfacing via SCPI using USB, Ethernet, or GPIB.
- Data streaming available using RS-422 serial interface.
- Internal data storage for up to one million measurements.
- Rugged design for manufacturing environments.

It's Our Business to be Exact!

(585) 924-2620
bristol-inst.com
info@bristol-inst.com

SPECIFICATIONS

828 Series

MODEL	828B	
OPTICAL SIGNAL	CW and modulated	
WAVELENGTH		
Range	1250 – 1650 nm (182 – 240 THz)	
Accuracy ^{1,2}	± 0.65 parts per million (± 1 pm at 1550 nm)	
Repeatability ^{3,4}	± 0.2 parts per million (± 0.3 pm at 1550 nm)	
Calibration ⁵	Automatic with built-in wavelength standard	
Display Resolution	0.0001 nm	
Units ⁶	nm, cm ⁻¹ , THz	
POWER		
Calibration Accuracy	± 0.5 dB (± 30 nm from 1310 and 1550 nm)	
Linearity ⁴	± 0.3 dB (1250 – 1600 nm)	
Polarization Dependence	± 0.5 dB (1250 – 1600 nm)	
Display Resolution	0.01 dB	
Units	dBm, mW	
OPTICAL INPUT SIGNAL		
Maximum Laser Bandwidth ⁷	10 GHz (80 pm at 1550 nm)	
Sensitivity ⁸	1 kHz: -25 dBm (3 μW) 500 Hz: -30 dBm (1 μW) 250 Hz: -35 dBm (0.3 μW) 100 Hz: -40 dBm (0.1 μW)	
Maximum Power	Displayed level Safe level	+ 10 dBm (10 mW) + 18 dBm (63 mW)
Return Loss ⁴	40 dB	
MEASUREMENT RATE/TIME ⁹	1 kHz streaming over RS-422 serial interface 5 ms (SCPI commands)	
INPUTS/OUTPUTS		
Optical Input	9/125 μm single-mode fiber (FC/UPC or FC/APC)	
Instrument Interface	Streaming via RS-422 (internal or external TTL trigger) Library of commands (SCPI) via USB 2.0, Ethernet, GPIB (optional) Internal data storage for up to 1 million measurements	
ENVIRONMENTAL ⁴		
Warm-Up Time	< 15 minutes	
Temperature	+15°C to +30°C (-10°C to +70°C storage)	
Pressure	500 - 900 mm Hg	
Humidity	≤ 90% R.H. at +40°C (no condensation)	
DIMENSIONS AND WEIGHT		
Dimensions (H x W x D)	3.5" x 17.0" x 15.0" (89 mm x 432 mm x 381 mm)	
Weight	16 lbs (7.2 kg)	
POWER REQUIREMENTS	90 - 264 VAC, 47 - 63 Hz, 50 VA max	

- (1) Defined as measurement uncertainty, or maximum wavelength error, using a coverage factor of 3 providing a confidence level of ≥ 99.7%.
- (2) Traceable to an NIST standard (SRM 2517a).
- (3) For a 10 minute measurement period given at three times the standard deviation (3σ).
- (4) Characteristic performance, but non-warranted.
- (5) Laser diode locked to acetylene absorption (NIST Special Publication 260-133).
- (6) Data in units of nm and cm⁻¹ are given as vacuum values.
- (7) Bandwidth is FWHM.
- (8) Dependent on frame rate of the photodetector array.
- (9) Measurement time using SCPI commands dependent on PC/network timing.



Bristol Instruments reserves the right to change the detail specifications as may be required to permit improvements in the design of its products. Specifications are subject to change without notice.