



上海尖丰光电技术有限公司

光纤耦合单模激光二极管(Fiber Coupled Single Mode Laser Diodes)

品牌 : Qphotonics

- 光纤耦合 Fabry Perot (FP)激光二极管
- 光纤耦合波长稳定的激光二极管与光纤布拉格光栅 (FBG) 和分布反馈 (DFB)
- 连续或脉冲运行
- 波长范围 405-1550nm
- 14 引脚双列直插或 14 引脚的蝴蝶包内置热敏电阻、热电冷却器和光电二极管
- 同轴和迷你 DIL 封装内置监控光电二极管
- 单模光纤尾纤
- 可选 FC / PC 或 FC/APC 连接器

详细的规格参数 :

峰值波长 (nm)	规格型号	典型功率	激光类型	封装	光谱宽度 (nm)	详细资料
375-995	QTFS-WHITE-LED	10mW	LED	Turnkey Source		Details
395-415	QFLD-405-20S	20mW	FP	14-pin Butterfly	1	Details
400-410	QTFS-405-LD-M	90mW	LD	Turnkey Source		Details
430-650	QTFS-450-630-LED	10mW	LED	Turnkey Source	20@Blue/Red	Details
440-460	QFLD-450-10S	10mW	FP	14-pin BTF	1	Details
510-530	QFLD-520-10S	10mW	FP	Butterfly	1	Details
625-645	QFLD-635-1SAX	1mW	FP	Co-axial	1	Details
630-645	QFBGLD-635-1	0.5mW	FBG	14-Pin DIL	500 kHz	Details
630-638	QFBGLD-633-30	30mW	FBG	Butterfly	500 kHz	Details



上海尖丰光电技术有限公司

631-635	QFLD-633-20S	20mW	FP	Butterfly	1	Details
631-636	QFLD-633-40S	40mW	FP	Butterfly	1	Details
632-638	QFLD-635-1S	1mW	FP	14-pin DIL	0.5	Details
633-642	QFLD-635-40S	40mW	FP	Butterfly	1	Details
640-660	QFLD-650-2AX	2mW	FP	Co-axial	2	Details
645-665	QFLD-660-20SAX	20mW	FP	Co-axial	1	Details
650-670	QTFS-660-LD	15	LD	Turnkey Source		Details
650-670	QFLD-660-20S	20mW	FP	14pin DIL	1	Details
650-670	QFLD-660-10S	10mW	FP	14-pin DIL	1	Details
650-660	QFLD-650-2S	1mW	FP	14-pin DIL	0.5	Details
650-670	QFBGLD-660-1	0.5mW	FBG	14-Pin DIL	500 kHz	Details
675-695	QFLD-685-15SAX	15mW	FP	Co-axial	1	Details
695-710	QFLD-700-20S	20mW	FP	Butterfly	1	Details
725-735	QFLD-730-20S	20mW	FP	Butterfly	1	Details
750-770	QFLD-760-3S	3mW	FP	14-pin DIL	0.5	Details
750-770	QFBGLD-760-5	5mW	FBG	14-Pin DIL	500 kHz	Details
758-764	QDMLD-760-5	5mW	DM	Butterfly	5MHz	Details
765-785	QFBGLD-775-5	5mW	FBG	14pin DIL	500 kHz	Details
770-780	QFLD-775-10SB	10mW	FP	Butterfly	1	Details
770-790	QFLD-780-20SAX	20mW	FP	Co-axial	1	Details
770-790	QFLD-780-100S	100mW	FP	Butterfly	1.5	Details
770-785	QFLD-780-10S	10mW	FP	14-pin DIL	1	Details
778-784	QDMLD-780-10	10mW	DM	Butterfly	2MHz	Details
785-805	QFLD-795-100S	100mW	FP	Butterfly	2	Details
785-796	QFLD-795-100S-PM	100mW	FP	Butterfly	0.5	Details
785-805	QFLD-795-50S	50mW	FP	14-pin DIL	1	Details
785-795	QFBGLD-790-5	5mW	FBG	14-Pin DIL	500 kHz	Details
791-799	QFBGLD-795-100	100mW	FBG	Butterfly	0.2	Details
800-813	QFLD-808-100S	100mW	FP	Butterfly	1	Details



上海尖丰光电技术有限公司

800-820	QFLD-810-10S	10mW	FP	14-pin DIL	2.5	Details
800-820	QFLD-808-50S	50mW	FP	14-pin DIL	2.5	Details
800-815	QFBGLD-808-5	5mW	FBG	14-Pin DIL	500 kHz	Details
804-812	QFBGLD-808-100	100mW	FBG	Butterfly	0.2	Details
810-830	QFLD-820-10S	10mW	FP	14-pin DIL	2.5	Details
820-840	QFLD-830-100S	100mW	FP	Butterfly	2	Details
820-840	QFBGLD-830-5	5mW	FBG	14-Pin DIL	500 kHz	Details
829-831	QFBGLD-830-100	100mW	FBG	Butterfly	0.2	Details
840-860	QFLD-850-100S	100mW	FP	Butterfly	1	Details
840-860	QFLD-850-100S-PM	100mW	FP	Butterfly	1	Details
840-860	QFLD-850-20S	20mW	FP	14-pin DIL	2	Details
840-860	QFBGLD-850-5	5mW	FBG	14-Pin DIL	500 kHz	Details
849-851	QFBGLD-850-100	100mW	FBG	Butterfly	0.2	Details
885-905	QFBGLD-895-2	2mW	FBG	14-Pin DIL	500 kHz	Details
895-915	QFLD-905-10S	10mW	FP	14-pin DIL	3	Details
895-920	QFLD-905-200S	200mW	FP	Butterfly	2	Details
905-925	QFBGLD-915-5	5mW	FBG	14-Pin DIL	500 kHz	Details
930-950	QFLD-940-200S	200mW	FP	Butterfly	1	Details
930-950	QFBGLD-940-200	200mW	FBG	Butterfly	0.3	Details
940-960	QFBGLD-950-5	5mW	FBG	14-Pin DIL	500 kHz	Details
945-975	QFLD-950-5S	5mW	FP	14-pin DIL	3	Details
960-985	QFLD-980-150S	150mW	FP	Butterfly	2.5	Details
960-990	QFLD-980-4SM	2mW	FP	Mini DIL	1.5	Details
960-985	QFLD-980-50S	50mW	FP	14-pin DIL	2.5	Details
965-985	QFBGLD-980-5	5mW	FBG	14-Pin DIL	500 kHz	Details
970-995	QFLD-980-10SAX	10mW	FP	Co-axial	1	Details
970-985	QFBGLD-980-200	200	FBG	Butterfly	0.5	Details



上海尖丰光电技术有限公司

970-985	QFBGLD-980-350	350mW	FBG	Butterfly	0.2	Details
970-985	QFBGLD-980-450	450mW	FBG	Butterfly	0.2	Details
975-982	QFBGLD-980-100U	100mW	FBG	Butterfly, no TEC	0.2	Details
975-985	QFBGLD-980-250	250mW	FBG	Butterfly	0.5	Details
990-1010	QFBGLD-1000-200	200mW	FBG	Butterfly	0.1	Details
1000-1100	QDFBLD-1060-20	20mW	DFB	Butterfly	3MHz	Details
1000-1130	QFLD-1030-400S	400mW	FP	Butterfly	2	Details
1000-1020	QFLD-1010-50S	50mW	FP	14-pin DIL	2.5	Details
1000-1130	QFBGLD-1060-400	400mW	FBG	Butterfly	0.1	Details
1005-1025	QFLD-1015-100S	100mW	FP	Butterfly	2.5	Details
1020-1040	QFLD-1030-30S	30mW	FP	14-pin DIL	2.5	Details
1020-1040	QFLD-1030-50S	50mW	FP	14-pin DIL	2.5	Details
1020-1040	QFBGLD-1030-5	5mW	FBG	14-Pin DIL	500 kHz	Details
1025-1035	QFLD-1030-100S	100	FP	Butterfly	2	Details
1028-1032	QDFBLD-1030-20	20mW	DFB	Butterfly	3MHz	Details
1030-1090	QFLD-1064-1200SP	1200mW	FP	Butterfly	1	Details
1035-1065	QFLD-1050-100S	100mW	FP	Butterfly	3	Details
1048-1058	QFBGLD-1053-5	5mW	FBG	14-Pin DIL	500 kHz	Details
1050-1070	QFTS-1060-LD	1	LD	Turnkey Source		Details
1050-1085	QFLD-1060-10S	10mW	FP	14-pin DIL	2	Details
1050-1075	QFLD-1060-200S	200mW	FP	Butterfly	3	Details
1050-1075	QFLD-1060-50S-BTF	50mW	FP	Butterfly	2	Details
1050-1090	QFLD-1055-600S	600mW	FP	Butterfly	1	Details
1050-1065	QTFL-1060-15	25mW	Tunable laser	Turnkey System	0.1	Details
1050-1075	QFBGLD-1060-100	100mw	FBG	Butterfly	0.3 nm	Details
1050-1075	QFBGLD-1060-150	150mW	FBG	Butterfly	0.3 nm	Details
1050-1080	QFBGLD-1060-200	200mW	FBG	Butterfly	0.3 nm	Details
1055-1075	QFLD-1060-30S-AR	30mW	Gain chip	14-pin DIL	2.5	Details
1055-1070	QFLD-1060-100S	100mW	FP	Butterfly	3	Details
1055-1075	QFLD-1060-150S	150mW	FP	Butterfly	2	Details
1055-1075	QFLD-1060-30S	30mW	FP	14-pin	2.5	Details



上海尖丰光电技术有限公司

				DIL		
1055-1075	QFLD-1060-40S	40mW	FP	14-pin DIL	2.5	Details
1055-1075	QFBGLD-1060-10	10mW	FBG	14-Pin DIL	500 kHz	Details
1055-1075	QFBGLD-1060-10BTF	10mW	FBG	Butterfly	500 kHz	Details
1055-1075	QFBGLD-1060-20	20mW	FBG	Butterfly	500 kHz	Details
1055-1075	QFBGLD-1060-20PM	20mW	FBG	Butterfly	1 MHz	Details
1055-1075	QFBGLD-1060-30PM	30mW	FBG	Butterfly	1 MHz	Details
1055-1075	QFBGLD-1060-40	40mW	FBG	Butterfly	1 MHz	Details
1055-1075	QFBGLD-1060-5	5mW	FBG	14-Pin DIL	500 kHz	Details
1055-1075	QFBGLD-1060-5PM-T	3mW	FBG	Butterfly	500 kHz	Details
1059-1069	QFLD-1064-600S	600mW	FP	Butterfly	4	Details
1062-1066	QDBRLD-1064-150	150mW	DBR	Butterfly	3MHz	Details
1063-1065	QDFBLD-1064-20	20mW	DFB	Butterfly	3MHz	Details
1063-1065	QFBGLD-1064-400	400mW	FBG	Butterfly	0.01-0.1	Details
1075-1090	QFLD-1080-30S	30mW	FP	14-pin DIL	3	Details
1075-1085	QFLD-1080-600S	600mW	FP	Butterfly	4	Details
1077-1082	QFBGLD-1080-2	2mW	FBG	14-Pin DIL	500 kHz	Details
1078-1082	QDFBLD-1080-20	20mW	DFB	Butterfly	3MHz	Details
1079-1081	QFBGLD-1080-400	400mW	FBG	Butterfly	0.1	Details
1121-1123	QFBGLD-1122-300	300mW	FBG	Butterfly	0.1	Details
1130-1170	QFBGLD-1150-300	300mW	FBG	Butterfly	0.1	Details
1140-1170	QFLD-1155-300S	300mW	FP	Butterfly	6月12日	Details
1165-1190	QFLD-1170-10S	10mW	FP	14-pin DIL	2	Details
1170-1190	QFLD-1177-350S	350mW	FP	Butterfly	10	Details
1170-1280	QFLD-1240-350S	350mW	FP	Butterfly	10	Details
1170-1190	QFBGLD-1177-350	350mW	FBG	Butterfly	0.1-1	Details
1170-1280	QFBGLD-1220-350	350mW	FBG	Butterfly	0.1-1	Details
1190-1280	QFLD-1231-350S	350mW	FP	Butterfly	10	Details
1200-1250	QFLD-1240-500S	500mW	FP	Butterfly	10	Details
1200-1250	QFLD-1240-550S	550mW	FP	Butterfly	10	Details
1200-1250	QFBGLD-1240-500	500mW	FBG	Butterfly	0.08-1.5	Details
1239-1241	QFBGLD-1240-350	350mW	FBG	Butterfly	0.08-1.5	Details
1260-1290	QFLD-1270-3S	3mW	FP	14-pin DIL	3	Details
1270-1330	QFLD-1300-2SM	2mW	FP	Mini DIL	3	Details



上海尖丰光电技术有限公司

1270-1330	QFBGLD-1300-5	5mW	FBG	14-pin DIL	500 kHz	Details
1280-1330	QFLD-1310-5SAX	4	FP	Co-axial	3	Details
1280-1330	QFLD-1300-300S	300mW	FP	Butterfly	6	Details
1280-1340	QFBGLD-1300-350	350mW	FBG	Butterfly	0.15-1.5	Details
1285-1330	QFLD-1310-2SAX	2	FP	Co-axial	3	Details
1288-1292	QDFBLD-1290-2	2mW	DFB	Co-axial	0.01	Details
1290-1330	QFLD-1300-1S	1.5mW	FP	14-pin DIL	2	Details
1290-1330	QFLD-1300-10S	10mW	FP	14-pin DIL	3	Details
1290-1310	QFLD-1300-150S	150mW	FP	Butterfly	7	Details
1290-1320	QDFBLD-1300-20	20mW	DFB	Butterfly	0.02	Details
1300-1320	QDFBLD-1300-10	10mW	DFB	Butterfly	0.02	Details
1300-1320	QDFBLD-1310-20DIL	20mW	DFB	14pins DIL	0.01	Details
1300-1320	QDFBLD-1310-2	2mW	DFB	Co-axial	0.01	Details
1300-1320	QDFBLD-1310-5AX	4mW	DFB	Co-axial	0.01	Details
1300-1315	QDFBLD-1300-5	5mW	DFB	14pins DIL	0.01	Details
1376-1400	QDMLD-1392-10	10mW	DM	Butterfly	2 MHz	Details
1385-1395	QDFBLD-1390-10	10mW	DFB	Butterfly	10MHz	Details
1420-1430	QFBGLD-1420-150	150mW	FBG	Butterfly	3	Details
1435-1455	QFLD-1440-200S	200mW	FP	Butterfly	8	Details
1435-1445	QFBGLD-1440-150	150mW	FBG	Butterfly	3	Details
1435-1445	QFBGLD-1440-350	350mW	FBG	Butterfly	3	Details
1450-1460	QFBGLD-1450-200	200mW	FBG	Butterfly	3	Details
1460-1470	QFBGLD-1460-150	150mW	FBG	Butterfly	3	Details
1460-1480	QFBGLD-1470-150	150mW	FBG	Butterfly	3	Details
1470-1495	QFLD-1490-150S	150mw	FP	Butterfly	6	Details
1470-1510	QDFBLD-1490-5	5mW	DFB	Co-axial	0.01	Details
1480-1500	QFLD-1490-5S	3mW	FP	14-pin DIL	1	Details
1480-1500	QDFBLD-1490-10DIL	10mW	DFB	14pin DIL	0.01	Details
1480-1500	QDFBLD-1490-20DIL	20mW	DFB	14pins DIL	0.01	Details
1485-1495	QFBGLD-1490-150	150mW	FBG	Butterfly	3	Details
1490-1510	QFLD-1500-200S	200mW	FP	Butterfly	6	Details
1506-1512	QDFBLD-1510-15	15mW	DFB	Butterfly	10MHz	Details



上海尖丰光电技术有限公司

1507-1513	QDFBSS-1510-5	5mW	DFB	Co-axial fiber coupled	< 0.01	Details
1520-1580	QFLD-1550-10SAX	10mW	FP	Co-axial	5	Details
1520-1540	QDFBLD-1530-20	20mW	DFB	Butterfly	10MHz	Details
1520-1540	QDFBLD-1530-5AX	4mW	DFB	Co-axial	0.01	Details
1525-1575	QFLD-1550-1SM	1.5mW	FP	Mini DIL	3	Details
1528-1570	QDFBLD-1550-5	5mW	DFB	Butterfly	2MHz	Details
1528-1565	QDFBLD-1550-100	100mW	DFB	Butterfly	1MHz	Details
1530-1570	QFLD-1550-2SAX	2mW	FP	Co-axial	3	Details
1530-1570	QFLD-1550-100S	100mW	FP	Butterfly	7	Details
1530-1570	QFLD-1550-10S	10mW	FP	14-pin DIL	4	Details
1530-1570	QFLD-1550-150S	150mW	FP	Butterfly	7	Details
1530-1570	QTFBGLD-1550-10	10mW	FBG	Butterfly	500 kHz	Details
1530-1565	QDFBLD-1550-2EM	2mW	DFB	Butterfly	2MHz	Details
1530-1550	QFBGLD-1550-100	100mW	FBG	Butterfly	0.1	Details
1530-1570	QDFBLD-1550-10	10	DFB	Butterfly	2MHz	Details
1530-1570	QDFBLD-1550-20	20mW	DFB	Butterfly	10MHz	Details
1530-1570	QDFBLD-1550-20DIL	20mW	DFB	DIL	0.01	Details
1530-1570	QDFBLD-1550-2	2mW	DFB	Co-axial	0.01	Details
1530-1050	QFBGLD-1550-50F	50mW	FBG	Butterfly	0.01	Details
1530-1570	QDFBLD-1550-5AX	4mW	DFB	Co-axial	0.01	Details
1535-1575	QFLD-1550-50S	50mW	FP	14-pin DIL	9	Details
1535-1555	QFBGLD-1550-150	150mW	FBG	Butterfly	1	Details
1540-1570	QFLD-1550-20S-AR	20mW	Gain chip	14-pin DIL	4	Details
1540-1565	QFLD-1550-20S	20mW	FP	14pin DIL	5	Details
1540-1560	QDFBLD-1550-2SM	2mW	DFB	Mini DIL	10MHz	Details
1540-1570	QDFBLD-1550-50	45mW	DFB	Butterfly	1MHz	Details
1560-1585	QFLD-1570-10S	10	FP	14-pin DIL	7	Details
1560-1580	QFLD-1570-5S	5mW	FP	14pin DIL	4	Details
1560-1580	QDFBLD-1570-5AX	4mW	DFB	Co-axial	0.01	Details
1570-1600	QDFBLD-1580-20	20mW	DFB	Butterfly	10MHz	Details
1570-1610	QDFBLD-1590-5	5mW	DFB	Co-axial	0.01	Details
1590-1620	QDFBLD-1600-20	20mW	DFB	Butterfly	10MHz	Details
1610-1635	QFLD-1620-2S	2	FP	14-pin	7	Details



上海尖丰光电技术有限公司

				DIL		
1615-1635	QFLD-1625-20S	20mW	FP	14pin DIL	5	Details
1615-1635	QFLD-1620-5S	4mW	FP	14-pin DIL	7	Details
1615-1640	QDFBLD-1625-10DIL	10mW	DFB	14pin DIL	0.01	Details
1625-1675	QFLD-1650-75S	75mW	FP	Butterfly	6	Details
1630-1670	QTFBGLD-1650-5	3mW	FBG	Butterfly	500 kHz	Details
1630-1660	QFBGLD-1650-5	3mW	FBG	DIL	10MHz	Details
1651-1656	QDMLD-1654-5	5mW	DM	Butterfly	2MHz	Details